

RANGER180

RANGER SERIES



WISE
ENERGY

askwise.com.au
1300 368 331

SPECIFICATIONS

Nominal Voltage	Available in custom configurations 51.2V or HV
Battery Manufacturer	SafeBatt
Storage Maximum Capacity	Upto 180kWhr SafeBatt Pro LFP
Inverter Output Capacity	Upto 90kVA
Maximum PV Voltage	450V
Maximum PV Input	34.5kW
Remote Monitoring	Ekrano GX
Component Brand	Victron
IP Rating	IP56
Compatible To Raise Solar STC	YES
Fitted Outlets	Hardwired
Material/Finish	Steel/Powdercoated (Woodland)

